

MMX-30 - Line Mixer



Compact 3-channel stereo line mixer

- 3 stereo input channels with one level control each
- 1 stereo master output, adjustable
- RCA connections for input channels and output
- 2 stereo headphone outputs, common control
- Signal/peak LEDs for the input channels and peak LED for the output

Tekniset tiedot:

| | |
|--------------------|--|
| No. of channels | : - |
| No. of inputs | : - |
| Mic input | : - |
| Line input | : 40Â mV, 3 x RCA L/R |
| CD input | : - |
| Phono input | : - |
| Tape (play) | : - |
| Aux input | : - |
| Insert input | : - |
| Effect return | : - |
| Master output | : 4Â V, 1 x RCA L/R |
| Record output | : - |
| Monitor output | : - |
| Booth output | : - |
| Aux output | : - |
| Insert output | : - |
| Effect send | : - |
| Control room | : - |
| Tape (rec) | : - |
| Headphones | : 2 x 10 mW/2 x 32Â Ohm, 2 x 6.3 mm jack |
| Gooseneck lamp | : - |
| WiFi | : - |
| USB | : - |
| Bluetooth | : - |
| Frequency range | : 5-30,000 Hz |
| THD | : < 0.1% |
| S/N ratio | : ? 66 dB |
| Crosstalk | : - |
| Equalizer bass | : - |
| Equalizer midrange | : - |
| Equalizer treble | : - |
| equalizer | : - |
| Talkover | : - |
| Phantom power | : - |
| Crossfader | : - |

| | |
|--|----------------------------------|
| Media player | : - |
| Amplifier | : - |
| Power supply | : via encl. plug-in power supply |
| Mains voltage | : - |
| Mains frequency | : - |
| Power consumption, operation | : - |
| Operating voltage (possible alternative) | : - |
| Power supply (possible alternative) | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Width | : 147 mm |
| Height | : 50 mm |
| Depth | : 119 mm |
| Rack spaces, RS | : - |
| Weight | : 693 g |