

## MMX-8 - Microphone Mixer



Miniature universal audio mixer

- 8 mono channels, switchable mic/line
- Selection of 4 stereo channels
- 2 output level controls, 2 peak LEDs
- Supplied w/o battery

## Tekniset tiedot:

|                    |                            |
|--------------------|----------------------------|
| No. of channels    | : -                        |
| No. of inputs      | : -                        |
| Mic input          | : 5Â mV, 8 x 6.3 mm jack   |
| Line input         | : 50Â mV, 8 x 6.3 mm jack  |
| CD input           | : -                        |
| Phono input        | : -                        |
| Tape (play)        | : -                        |
| Aux input          | : -                        |
| Insert input       | : -                        |
| Effect return      | : -                        |
| Master output      | : 100Â mV, 2 x 6.3 mm jack |
| Record output      | : -                        |
| Monitor output     | : -                        |
| Booth output       | : -                        |
| Aux output         | : -                        |
| Insert output      | : -                        |
| Effect send        | : -                        |
| Control room       | : -                        |
| Tape (rec)         | : -                        |
| Headphones         | : -                        |
| Gooseneck lamp     | : -                        |
| WiFi               | : -                        |
| USB                | : -                        |
| <b>Bluetooth</b>   | : -                        |
| Frequency range    | : 20-20,000Â Hz            |
| THD                | : < 0.4%                   |
| S/N ratio          | : 55 dB                    |
| Crosstalk          | : -                        |
| Equalizer bass     | : -                        |
| Equalizer midrange | : -                        |
| Equalizer treble   | : -                        |
| equalizer          | : -                        |
| Talkover           | : -                        |
| Phantom power      | : -                        |
| Crossfader         | : -                        |

|  |  |
|--|--|
| Media player                             | : -  |
| Amplifier                                | : -  |
| Power supply                             | : 9Â V battery or via optional power supply PSS-600E |
|  |  |
| Mains voltage                            | : -  |
| Mains frequency                          | : -  |
| Power consumption, operation             | : -  |
| Operating voltage (possible alternative) | : -  |
| Power supply (possible alternative)      | : -  |
| Admiss. ambient temp.                    | : 0-40 °C  |
| Width                                    | : 150 mm   |
| Height                                   | : 68 mm  |
| Depth                                    | : 115 mm   |
| Rack spaces, RS                          | : -  |
| Weight                                   | : 550 g  |