

## LSIP-68/2 - Air Coil



Air core coil, 0.68 mH

0.85 mm wire for constructing high-quality hi-fi crossover networks, also of very high quality as parallel coil.

## Tekniset tiedot:

|                           |                               |
|---------------------------|-------------------------------|
| Description               | : air core coil               |
| Nominal value             | : 0.68 mH                     |
| Rated voltage             | : -                           |
| Power rating              | : 100 W                       |
| Frequency range           | : -                           |
| Housing                   | : -                           |
| Colour/colour coding      | : -                           |
| Enam. copper wire(CUL)    | : $\sim 0.85$ mm              |
| DC resistance             | : 0.55 Ohm                    |
| Saturation current(50 Hz) | : -                           |
| Primary                   | : -                           |
| Secondary                 | : -                           |
| Pin spacing               | : -                           |
| Packing unit              | : 1                           |
| Dimensions                | : $\sim 48$ mm x $\sim 19$ mm |
| Weight                    | : 90 g                        |
| Pos.                      | : -                           |
| Other features            | : -                           |