

MMX-11USB - Mixer



2-channel miniature audio mixer,
with 3 inputs and USB interface.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 1 mono input channel with gain control, 2-way equalizer and pan pot, peak LED
- 1 stereo input channel with level control, 2-way equalizer and balance control
- Tape record/play connections
- 1 x 3.5 mm stereo output (master)
- Adjustable headphone output
- +20 V phantom power, permanent
- Clip LED
- Robust metal housing of compact size

Tekniset tiedot:

No. of channels	: 2
No. of inputs	: 3
Mic input	: 0.5 mV, 1 x 3-pole XLR
Line input	: 150 mV (stereo), 1 x RCA L/R 2 mV (mono), 6.3 mm jack
CD input	: -
Phono input	: -
Tape (play)	: 420 mV, 1 x RCA L/R
Aux input	: -
Insert input	: -
Effect return	: -
Master output	: 6 V max., 1 x 3.5 mm jack
Record output	: -
Monitor output	: -
Booth output	: 6 V max., 1 x 3.5 mm jack
Aux output	: -
Insert output	: -
Effect send	: -
Control room	: -
Tape (rec)	: 1 x RCA L/R
Headphones	: -
Gooseneck lamp	: -
WiFi	: -
USB	: yes
Bluetooth	: -
Frequency range	: 20-20,000 Hz
THD	: < 0.05%
S/N ratio	: 81 dB, weighted
Crosstalk	: -
Equalizer bass	: ± 15 dB/80 Hz
Equalizer midrange	: -
Equalizer treble	: ± 15 dB/12 kHz
equalizer	: -
Talkover	: -
Phantom power	: +20 V
Crossfader	: -

Media player	: -
Amplifier	: -
Power supply	: via USB interface or via encl. power supply
Mains voltage	: -
Mains frequency	: -
Power consumption, operation	: -
Operating voltage (possible alternative)	: DC 5 V
Power supply (possible alternative)	: DC 500 mA
Admiss. ambient temp.	: 0-40 °C
Width	: 102 mm
Height	: 45 mm
Depth	: 140 mm
Rack spaces, RS	: -
Weight	: 430 g