

# ADP-DAI-1X0 - Dante Adaptor



Dante(r) AVIO analogue input adapter (1-channel)

- For connecting analogue audio line level devices (e.g. mixer) to a Dante(r) audio network
- Adjustable signal level: +24/+4/0 dBu, 0/-10 dBV (via Dante(r) controller)
- Frequency range: 20-20,000 Hz
- Impedance: 20 kOhm (bal.), 10 kOhm (unbal.)
- Dynamic range: > 100 dB
- S/N ratio: > 100 dB
- THD: < 0.01%
- Sampling rates: 44.1/48/96 kHz, 24 bits
- Connections: 1 x RJ45, 1 x XLR inline jack

The brand Dante(r) as well as the Dante(r) software which may have been integrated into these products are licenced by Audiante Pty Ltd.

## Tekniset tiedot:

Description	: Dante <sup>(n)</sup> AVIO analogue input adapter
Nominal value	: -
Type	: 1-channel
Colour	: black
Material	: -
Suitable for	: -
Power supply	: PoE
Admiss. ambient temp.	: -
Dimensions	: -
Length	: -
Mounting dimensions	: -
Weight	: 120 g
Connections	: 1 x RJ45, 1 x 3-pole XLR inline jack
Other features	: -
Packing unit	: 1