

## MPX-622/SW - Stereo Mixer



6-channel stereo audio mixer,  
particularly suitable for PA and DJ applications.

- 2 mono microphone channels with talkover switch and 2-way tone control
- 4 stereo input channels, switchable phono/line (channels 1 and 2) or line/line (channels 3 and 4)
- 1 stereo master output
- 1 stereo record output, independent of the master
- 3-way equalizer with centre click for master output and record output
- Pre-fader listening to each stereo input channel and the master output via adjustable stereo headphone output
- Switchable crossfader for crossfading between channels 1-4, any assignment possible
- Stereo LED level display

## Tekniset tiedot:

|                    |                                |
|--------------------|--------------------------------|
| No. of channels    | : 6                            |
| No. of inputs      | : 8                            |
| Mic input          | : 1 mV, 2 x 6.3 mm jack        |
| Line input         | : 150 mV, 5 x RCA L/R          |
| CD input           | : 150 mV, 1 x RCA L/R          |
| Phono input        | : 3 mV, 2 x RCA L/R            |
| Tape (play)        | : -                            |
| Aux input          | : -                            |
| Insert input       | : -                            |
| Effect return      | : -                            |
| Master output      | : 0.775 V/600 Ohm, 1 x RCA L/R |
| Record output      | : 0.775 V/600 Ohm, 1 x RCA L/R |
| Monitor output     | : -                            |
| Booth output       | : -                            |
| Aux output         | : -                            |
| Insert output      | : -                            |
| Effect send        | : -                            |
| Control room       | : -                            |
| Tape (rec)         | : -                            |
| Headphones         | : ? 8 Ohm, 1 x 6.3 mm jack     |
| Gooseneck lamp     | : -                            |
| WiFi               | : -                            |
| USB                | : -                            |
| <b>Bluetooth</b>   | : -                            |
| Frequency range    | : 20-20,000 Hz                 |
| THD                | : 0.1%                         |
| S/N ratio          | : 65 dB                        |
| Crosstalk          | : -                            |
| Equalizer bass     | : $\pm 10$ dB/100 Hz           |
| Equalizer midrange | : $\pm 10$ dB/1 kHz            |
| Equalizer treble   | : $\pm 10$ dB/10 kHz           |
| equalizer          | : -                            |
| Talkover           | : -15 dB                       |
| Phantom power      | : -                            |
| Crossfader         | : yes                          |

|  |                              |
|--|------------------------------|
| Media player                             | : -                          |
| Amplifier                                | : -                          |
| Power supply                             | : &acd; 230Â V/50Â Hz/10Â VA |
| Mains voltage                            | : &sim; 230 V                |
| Mains frequency                          | : 50 Hz                      |
| Power consumption, operation             | : 10 VA                      |
| Operating voltage (possible alternative) | : -                          |
| Power supply (possible alternative)      | : -                          |
| Admiss. ambient temp.                    | : 0-40 °C                    |
| Width                                    | : 482 mm                     |
| Height                                   | : 89 mm                      |
| Depth                                    | : 95 mm                      |
| Rack spaces, RS                          | : 2                          |
| Weight                                   | : 2.4 kg                     |